

# Bellman Neckloop

## BE9159



### Features

- 1 **High output power**  
Dual channel output
- 2 **Safety breakaway neck strap**  
To avoid strangulation
- 3 **Replaceable soft fabric tube**  
For comfort and hygiene
- 4 **Soft spray-coated housing**  
For increased comfort
- 5 **Silicone cable material**  
For easy handling
- 6 **Tie-clip**  
For correct positioning
- 7 **Gold plated plugs**  
To avoid corrosion

## Discreet and powerful

For high quality listening with hearing instruments. The Bellman® Neckloop works with any sound source with a 3.5 mm headphones output. Simply plug the Bellman® Neckloop into your speech amplifier, MP3 player, computer or cell phone and switch your hearing instruments to "T" position. The Bellman® Neckloop is discreet and comfortable, and can easily be worn under your shirt.

### Technical specifications

- Neck strap length 70 cm, 2.3 ft
- Cable length 90 cm, 2.9 ft
- Neckloop diameter 22 cm, 8.7 "

### Size housing

- Width 3.5 cm, 1.4 "
- Height 4.0 cm, 1.6 "
- Thickness 1.0 cm, 0.4 "
- Weight 60 g, 2.1 oz

### Output

- 1500 mA/m @ 15 cm / 6 " distance and 2 x 50 mW input signal

### Input

- 3.5 mm tele plug (stereo) gold plated connector, 90 degrees angle
- Impedance: 2 x 5 ohm

